

Transformer 200 VA with terminal blocks



Safety-transformer, with primary and secondary fuse

(Photo shows similar transformer but with different power)

Type-no. 096 052 200

Type Safety transformer

Intended use Low-voltage-halogen-lighting

Voltage Primary 230 V / Secondary 11.6 V AC

Power 200 VA

Input Wire (60 cm), fuse and overheat-protection

Output 4 x 50 W, each with fuse and terminal block

Size / weight 130 x 120 x 100 mm / 3.1 kg

Approvals C E M/M

Origin Made in Germany

Standard delivery time 1-2 weeks