

## Transformer 50 VA with Wieland-socket



Safety-transformer, with primary and secondary fuse

(Photo shows similar transformer but with different power)

Type-no.	066 085 050
Туре	Safety transformer
Intended use	Low-voltage-halogen-lighting
Voltage	Primary 230 V / Secondary 11.6 V AC
Power	50 VA
Input	Wire (60 cm), fuse and overheat-protection
Output	1 x 50 W with fuse and wire (60 cm) with Wieland-socket
Size / weight	87 x 60 x 62 mm / 1.0 kg
Approvals	<b>CE WW</b>
Origin	Made in Germany
Standard delivery time	1-2 days